



Desktop Dual Charger for ASCOM d62/i62 DECT Wireless Handset with Patented Dock-in-Case® Solution

Product ID:AS62AUDA



zAdapter® AS62AUDA Desktop Dual Charger Set for ASCOM d62/i62 Wireless Handset to charge phone and spare battery at the same time. Keeps phone charged and ready for continuous use over an extended period of time without ever running out of power.

- The ONLY Dock-in-Case Desk Top Dual Charger for Ascom d62/i62 Wireless Handset
- Completed compliance with environment and safety standards
- Charges phone and spare battery at the same time
- Designed with patented Dock-In-Case® solution which allows users to charge phone with or without zCover carrying case on
- Full access to keypad allows phone to be dialed while docked
- Easy to use, monitor phone charging process on phone screen and battery charging process with LED indicators on charger
- Directs more power to charge the phone first
- Switches to a trickle charge when battery is full
- Safety first, intelligent battery temperature monitor discontinues charging when battery temperature reaches 113° F (45°C)
- High powered, fast charging with two times more output than other power supplies
- Can be placed on a desk or mounted on the wall to save space
- Unified Desktop Dual Charger is part of zCover Unified Modular Docking System. It can be docked into zCover Unified Dock Racks to form a Multi-Charger or customize a mixed Multi-charger with other Unified Desktop Dual Chargers or Unified Multi-battery Chargers

Patented Dock-in-Case® Solution for ASCOM d62/i62 Wireless Handset



The zAdapter® AS62AUDA Desktop Charger can be placed on a desktop or mounted on the wall

Specifications	
Dimensions (L x W x H)	9in x 5in x 3in 229mm x 127mm x 76mm
Weight	454g; 1lb
Power Supply	INPUT : AC100-240V 50/60Hz 0.50A ; OUTPUT: DC5.0V 1500mA
Operating Temperature	32°F to 113°F (0°C to 45°C)
Storage Temperature	-22°F to 140°F (-30°C to 60°C)
Relative Humidity	10 to 95% (no condensing)
Charging Time	Use zAdapter power supply: Spare battery only: 2 hours (standard battery pack) Battery installed in phone (phone powered off): 2 hours (standard battery pack) Battery installed in phone (powered off) and a spare battery: 3 hours (standard battery pack)
What's in the box:	1 x AS62AUAK zAdapter Desktop Dual Charger 1 x ZDAC15AK zAdapter® AC to DC 5V 1.5 USB power adapter 1 x ZDACAT (XX) = Your choice of plug connector XX = AU (Australia), EU (Continental Europe), JP (Japan), NA (North America), UK (United Kingdom) & CN (China)

Part ID Number	Description
AS62AUDA-NA=	Desktop Dual Charger Set for ASCOM d62/i62 Wireless Handset, with North America Plug Connector
AS62AUDA-AU=	Desktop Dual Charger Set for ASCOM d62/i62 Wireless Handset, with Australia Plug Connector
AS62AUDA-JP=	Desktop Dual Charger Set for ASCOM d62/i62 Wireless Handset, with Japan Plug Connector
AS62AUDA-UK=	Desktop Dual Charger Set for ASCOM d62/i62 Wireless Handset, with United Kingdom Plug Connector
AS62AUDA-EU=	Desktop Dual Charger Set for ASCOM d62/i62 Wireless Handset, with Continental Europe Plug Connector
AS62AUDA-CN=	Desktop Dual Charger Set for ASCOM d62/i62 Wireless Handset, with China Plug Connector

Related zCover Products



Unified 3 Batteries
Charger



Unified 3 slots
Multi-Charger



Unified 5 slots
Multi-Charger



Unified Desktop
Dual Charger



Unified 3 slots
Multi-Charger



Unified 5 slots
Multi-Charger



Ruggedized
Silicone Case



Desktop Dual Charger
Docking Cup



zCover Logo
Screen Wiper



Wallmount for Desktop
Battery Charger



Wallmount for Battery
Gang Charger



Wall Mount Kit



Cleaning Wet
Wipes



Bluetooth Speaker
Phone



Tech Lanyard

zCover, Inc.

Tel: (604)273-3003 Fax: (604)273-3023

PO & Sales Support: sales@zcover.com

100-13551 Verdun Place Richmond, BC,

Canada V6V 1W5

Purchase Online: www.zcover.com