



Desktop Dual Charger for ASCOM d81 DECT Handset & Battery with Patented Dock-in-Case® Solution

Product ID:AS81AUDA



zAdapter® AS81AUDA Desktop Dual Charger Set for ASCOM d81 DECT Handset & Battery charges phone and spare battery at the same time. Keeps phone charged and ready for continuous use over an extended period of time without ever running out of power.

- Completed compliance with environment and safety standards
- Charges phone and spare battery at the same time
- Designed with patented Dock-In-Case® solution which allows user to charge phone with or without zCover carrying case
- Full access to keypad allows phone to be dialed while docked
- Easy to use, monitor phone charging process on phone screen and battery charging process with LED indicators on charger
- Directs more power to charge the phone first
- Switches to a trickle charge when battery is full
- Safety first, intelligent battery temperature monitor discontinues charging when battery temperature reaches 113° F (45°C)
- High powered, fast charging with two times more output than other power supplies
- Can be placed on a desk or mounted on the wall to save space
- Unified Desktop Dual Charger is part of zCover Unified Modular Docking System. It can be docked into zCover Unified Dock Racks to form a Multi-Charger or customize a mixed Multi-charger with other Unified Desktop Dual Chargers or Unified Multi-battery Chargers



The zAdapter® AS81AUDA Desktop Charger can be placed on a desktop or mounted on the wall

Specifications	
Dimensions (H x W x D)	9in x 5in x 3in 229mm x 127mm x 76mm
Weight	454g; 1lb
Power Supply	INPUT : AC100-240V 50/60Hz 0.50A ; OUTPUT: DC5.0V 1500mA
Operating Temperature	32°F to 113°F (0°C to 45°C)
Storage Temperature	-22°F to 140°F (-30°C to 60°C)
Relative Humidity	10 to 95% (no condensing)
Charging Time	Use zAdapter power supply: Spare battery only: 2 hours (standard battery pack) Battery installed in phone (phone powered off): 2 hours (standard battery pack) Battery installed in phone (powered off) and a spare battery: 3 hours (standard battery pack)
What's in the box:	1 x AS81AUAK zAdapter Desktop Dual Charger 1 x AS81ACUP zAdapter® AS81A Desktop Dual Charger Docking Cup ONLY 1 x ZDAC15AK zAdapter® AC to DC 5V 1.5 USB power adapter 1 x ZDACAT (XX) = Your choice of plug connector XX = AU (Australia), EU (Continental Europe), JP (Japan), NA (North America), UK (United Kingdom) & CN (China)

Part ID Number	Description
AS81AUDA-NA=	Desktop Dual Charger Set for ASCOM d81 DECT Handset & Battery, with North America Plug Connector
AS81AUDA-AU=	Desktop Dual Charger Set for ASCOM d81 DECT Handset & Battery, with Australia Plug Connector
AS81AUDA-JP=	Desktop Dual Charger Set for ASCOM d81 DECT Handset & Battery, with Japan Plug Connector
AS81AUDA-UK=	Desktop Dual Charger Set for ASCOM d81 DECT Handset & Battery, with United Kingdom Plug Connector
AS81AUDA-EU=	Desktop Dual Charger Set for ASCOM d81 DECT Handset & Battery, with Continental Europe Plug Connector
AS81AUDA-CN=	Desktop Dual Charger Set for ASCOM d81 DECT Handset & Battery, with China Plug Connector

Related zCover Products



zCover, Inc.
Tel: (604)273-3003 Fax: (604)273-3023
PO & Sales Support: sales@zcover.com
100-13551 Verdun Place Richmond, BC,
Canada V6V 1W5
Purchase Online: www.zcover.com